



All the patents are held accountable counterfeiting.

Features

Green Power



- Standard/Din Rail Mounting Dual Purpose
- Easy mounting (one-step installation)
- No-load Consumption is lower than 0.5W (No Display)
- Comply with High Efficiency Power 80Plus Criterion
- Comply with 2010. Energy Conservation Power Erp Regulation
- " Output Voltage Monitor " Display (Optional)
- Convection cooled high reliability
- 100% burn-in test
- 1 years warranty
- Output modify range: 3V~200VDC

DIMENSIONS:100(H)*83(D)*49(W)mm

WEIGHTS: 365g

General specifications

INPUT

Input range 90~132/180~264VAC(Selectable)
220~380VDC
Input frequency 47~63Hz
Inrush current (25°C) 20A/110VAC
40A/220VAC

OUTPUT

Hold-up time 13ms
Short protection Autorecovery
Over load protection Automatic power limited
Optional 5V/3A AUX output
for models which output voltage lower than 40VDC

Detail specifications

100 Watts

MODEL	O/P Volt Adj. ± %	Load(Current) ¹			Ripple & Noise ⁴	Line REG. ²	Load REG. ³	Efficiency ⁵	O.V.P
		Min.	Rated	Max.					
LP1100D-12M	V : +12V ±10%	0A	8.3A	8.3A	120mV	±1%	±1%	85% Ref.	17.1 ~ 18.9V
LP1100D-24M	V : +24V ±10%	0A	4.2A	4.2A	240mV	±1%	±1%	86% Ref.	31.4 ~ 34.7V
LP1100D-48M	V : +48V ±10%	0A	2.1A	2.1A	480mV	±1%	±1%	87% Ref.	64.6 ~ 71.4V

Please Choose Fit Function, And Fill In The Blank With Suitable Words.

Order Model: LP1100D-24M

Optional Function:

Terminal Block: " " : PCB Barrier Terminal Block
"E" : Mini Terminal BlockMonitor: " " : No Monitor
"D" : Monitor DisplayType: " " : No Display Function
"A" : Output Voltage Display

CE Standards

EN 55032, EN 55024,
EN 61000-3-3, (EN 61000-4-2,
EN 61000-4-3, EN 61000-4-4,
EN 61000-4-5, EN 61000-4-6,
EN 61000-4-8, EN 61000-4-11)
LVD: EN 60950-1

Safety Standards



UL 508 APPROVAL



CE Marking

Environments

Operating Temperature -15 ~ 50°C, Ambient
Operating Humidity 20 ~ 90% RH, No Condensing
Storage Temperature -20 ~ 85°C, Ambient
Vibration 2G, 10~500Hz, 3 axes

NOTE

1. Each output can provide up to maximum load, but total load can not exceed rated output power.
2. Line regulation is measured from low line to high line at rated load.
3. Load regulation is measured from 20% to 100% of rated load at 220VAC input.
4. Ripple & Noise are measured with 20MHz oscilloscope at 220VAC by using a 20cm long 12" twisted pair-wire with a 0.1uF/630V metal capacitor & a 47uF electrolytic capacitor parallel on the test point.
5. Efficiency is measured at rated load and 220VAC input.
6. Hold-up time is measured at rated load and 220VAC input.
7. With ● are CE safety approval, but no UL safety approval.
8. Output voltage monitor display models. no-load power consumption of 1.5W. and no Energy Conservation Power Erp Regulation.
9. Output Voltage Adjustable is measured on 5% of rated load.
10. Reign Power reserve the right to change specifications at any time without notice.

WEB : <http://www.switching-powers.com>
E-mail : rp21003f@ms7.hinet.net

Tel : 886-2-22997550
Fax : 886-2-22997596

REIGNPOWER
S.M.P.S